

E650 meter



1. Display scroll buttons

*scroll up button

*scroll down button

The readings on the display change approximately every 10 seconds. The reading identifier indicates which reading is currently displayed. If necessary, you can scroll the readings using the scroll button on the screen as follows:

1. Press either scroll button briefly until 88888888 appears on the display.
2. Press the scroll button again until the text Std_dAtA appears on the display.
3. Press the scroll button for more than 3 seconds until the reading identifier 1.8.1 appears on the display.

Now you can browse the energy readings of the same tariff for the last three months by briefly pressing the scroll down button. After these values, the tariff changes and you can browse the next tariff's readings for the next three months, as instructed. By pressing the scroll up button on the 1.8.1 screen, you can quickly read the instantaneous values.

The display returns to its initial state approximately one minute after the last button press. You can also restore the initial state by briefly pressing both scroll buttons simultaneously.

Reading the display

Normal status of the display:



Reading identifier

Energy reading

Reading identifiers:

0.9.1 time

0.9.2 date

1.8.1 total energy reading

If the display shows an F.F error code, please contact Oulun Energia Sähköverkko Oy's measurement manager, tel. +358 44 703 3262